

MCU Protocol (T)Error

Klipper reports: ERROR

MCU Protocol error

This is frequently caused by running an older version of the firmware on the MCU(s). Fix by recompiling and flashing the firmware.

Your Klipper version is: v0.12.0-102-g9f41f53c

MCU(s) which should be updated:

mcu: Current version v0.12.0-85-gd785b396

EBBCan: Current version v0.12.0-58-g25bc649c

RPi: Current version v0.12.0-58-g25bc649c

Up-to-date MCU(s):

<none>

Once the underlying issue is corrected, use the "RESTART" command to reload the config and restart the host software.

```
mcu 'EBBCan': Command format mismatch: query_adxl345 oid=%c rest_ticks=%u vs
query_adxl345 oid=%c clock=%u rest_ticks=%u
```

YouTube Video #86



- Letzte Version vor ADXL Update → v0.12.0-75-g94719fe3
- Update der ADXL MCU reicht

Recover

- `cd ~/klipper`
- `git checkout 94719fe → v0.12.0-75-g94719fe3`
- `sudo reboot`
- ggf. Detached → Soft Recovery



- `sudo reboot`

ADXL aus

- ADXL deaktivieren ... Sollte auch wieder zum Normalstand führen

Sicherung

- bestehende Sicherung zurückspielen

Updates machen

From:

<https://drklipper.de/> - Dr. Klipper Wiki

Permanent link:

https://drklipper.de/doku.php?id=klipper_faq:mcu_protocol_t_error&rev=1706723624

Last update: **2024/01/31 18:53**

